

					
	DINA-DR1-LITE	DINA-DR1	DINA-SR1	DINA-DR2-LITE	DINA-DR2
DMX Channel	2*512 (exp. to 6*512)	6*512	6*512	1*512 (exp. to 3*512)	2*512 (exp. to 3*512)
ArtNet (eDMX)	✓ exp. to 16*512	✓ exp. to 16*512	✓ exp. to 16*512		
Zones	20	20	20	5	5
Scenes	2000	2000	2000	99	99
DMX Port	Screw	Screw	XLR3	Screw	Screw
Connection	USB/RJ45	USB/RJ45	USB/RJ45	USB/RJ45	USB/RJ45
Memory	16 MB	16 MB	16 MB		
SD Card	32G Max.	32G Max.	32G Max.	32G Max.	32G Max.
ESAPRO2	PC/Mac	PC/Mac	PC/Mac	PC/Mac	PC/Mac
ESA2	PC/Mac	PC/Mac	PC/Mac	PC/Mac	PC/Mac
Remote APP	iOS/Android	iOS/Android	iOS/Android	iOS/Android	iOS/Android
Dry Port	8	8	8	8	8
Time Trigger	✓	✓	✓	✓	✓
UDP Remote	✓	✓	✓	✓	✓
RS232	Option	✓	✓		
DALI	Option	✓	✓		
SPI LED	Option	✓	✓		
Audio In	Option	✓	✓		
RDM	✓	✓	✓	✓	✓
NA Cloud	Option	✓	✓	Option	✓
Power Input	8-15V DC	8-15V DC	5-5.5V DC	8-15V DC	8-15V DC
Dimension (mm)	160*91*62	160*91*62	240*115*44	106*91*59	106*91*59
Installation	DIN-Rail	DIN-Rail	1U Rack	DIN-Rail	DIN-Rail
Weight	317g	317g	950g	180g	180g



Note:

1. DMX Channels, ArtNet Channels, Audio In functions can be upgraded as need.
2. All interfaces come with SUT (Smart Upgrade Technology). Add DMX Channels and upgrade to future software versions without the need to exchange the device.