


SUNLITE-BC

SUNLITE-EC

SUNLITE-FC

SUNLITE-RC
Live Use

DMX Channel	256 (exp. to 512)	2*512 (exp. to 4*512)	3*512 (exp. to 4*512)	6*512 (exp. to 8*512)
ArtNet Channel	Option	Option	512	10240 (20x512)
Sunlite Suite3 (PC)	Express	Express	Full	Full
Sunlite Suite2 (PC)	Express	Express	Full	Full
ESA2 (PC/Mac)	Option	✓	✓	✓
MIDI Trigger	✓	✓	✓	✓
Button		10		

Stand Alone Use

DMX Channel	128 (exp. to 512)	512 (exp. to 4*512)	512 (exp. to 4*512)	512 (exp. to 4*512)
Memory	64k	TF Card	TF Card	SD Card
Zones/Scenes	1/99	5/99	5/99	1/99
Time Triggering		Option	✓	✓
Button	3	13	3	3
Dry Contact Port		16		16

Basic

Housing	Plastic	Plastic	Meta	Meta(1U Rack)
Connection	USB	USB/Ethernet	USB/Ethernet	USB/Ethernet
USB Type	Type-C	Type-C	Type-B	Type-B
RDM Manager	Option	Option	✓	✓


Note:

1. In Express mode, the music light show function and MIDI timecode synchronization function are not available;
2. All interfaces come with SUT (Smart Upgrade Technology). Add DMX Channels and upgrade to future software versions without the need to exchange the device.